


## Calibration

**Calibrate (vt) :** 1. to determine the caliber of (as a thermometer tube); 2. to determine, rectify, or mark the gradations of (as a thermometer tube); 3. to standardize (as a measuring instrument) by determining the deviation from a standard so as to ascertain the proper correction factors; 4. ADJUST, TUNE

601.455/655 Copyright R. H. Taylor 1999-2023

1


## Calibration



601.455/655 Copyright R. H. Taylor 1999-2023

2

## Calibration



601.455/655 Copyright R. H. Taylor 1999-2021

3

## Basic Techniques


- **Parameter Estimation**
- **Mapping the space**

601.455/655 Copyright R. H. Taylor 1999-2023

4

## Parameter Estimation


- Compare observed system performance to reference standard (“ground truth”)
- Compute parameters of mathematical model that minimizes residual error.



601.455/655 Copyright R. H. Taylor 1999-2021

5


## Pointing device calibration



601.455/655 Copyright R. H. Taylor 1999-2021

6


## Pointing device calibration



601.455/655 Copyright R. H. Taylor 1999-2021

7


## Pointing device calibration



600.445 Copyright © R. H. Taylor 1999-2021

8


## Pointing device calibration



600.445 Copyright R. H. Taylor 1999-2021

9

## Pointing device calibration



601.455/655 Copyright R. H. Taylor 1999-2021

10

## Parameter estimation

Typically, try to find the minimum of a convex function such as

$$\bar{\mathbf{q}}^* = \underset{\bar{\mathbf{q}}}{\operatorname{argmin}} E\left(\left\{\bar{\mathbf{f}}(\bar{\mathbf{x}}_k; \bar{\mathbf{q}}), \bar{\mathbf{p}}_k\right\}\right)$$

for a function  $\bar{\mathbf{f}}(\bar{\mathbf{x}}; \bar{\mathbf{q}})$  and observations  $\bar{\mathbf{p}}_k = \bar{\mathbf{f}}(\bar{\mathbf{x}}_k; ?)$

There are many methods for solving this problem. You can consult any good numerical methods text, such as *Numerical Methods in C / C ++ / xyz*.

Most often  $E\left(\left\{\bar{\mathbf{f}}(\bar{\mathbf{x}}_k; \bar{\mathbf{q}}), \bar{\mathbf{p}}_k\right\}\right)$  is a sum of squares

$$E\left(\left\{\bar{\mathbf{f}}(\bar{\mathbf{x}}_k; \bar{\mathbf{q}}), \bar{\mathbf{p}}_k\right\}\right) = \sum_k \|\bar{\mathbf{f}}(\bar{\mathbf{x}}_k; \bar{\mathbf{q}}) - \bar{\mathbf{p}}_k\|^2$$

However, other functions are also used, e.g.

$$E\left(\left\{\bar{\mathbf{f}}(\bar{\mathbf{x}}_k; \bar{\mathbf{q}}), \bar{\mathbf{p}}_k\right\}\right) = \sum_k \|\bar{\mathbf{f}}(\bar{\mathbf{x}}_k; \bar{\mathbf{q}}) - \bar{\mathbf{p}}_k\|_{L_1}$$

$$E\left(\left\{\bar{\mathbf{f}}(\bar{\mathbf{x}}_k; \bar{\mathbf{q}}), \bar{\mathbf{p}}_k\right\}\right) = \sum_k -\log(\Pr(\bar{\mathbf{f}}(\bar{\mathbf{x}}_k; \bar{\mathbf{q}}) = \bar{\mathbf{p}}_k))$$

601.455/655 Copyright R. H. Taylor 1999-2021

11

## Linear Parameter Estimation

$\mathbf{p}_{nom} = \mathbf{f}(\mathbf{q})$  where  $\mathbf{q} = [q_1, \dots, q_n]^T$  are parameters

$$\mathbf{p}^* = \mathbf{f}(\mathbf{q} + \Delta \mathbf{q})$$

$$\approx \mathbf{f}(\mathbf{q}) + \begin{bmatrix} \ddots & \vdots \\ \cdots & \frac{\partial f_i}{\partial q_j}(\mathbf{q}) & \cdots \\ \vdots & \ddots \end{bmatrix} \begin{bmatrix} \Delta q_1 \\ \vdots \\ \Delta q_n \end{bmatrix}$$

$$\mathbf{p}^* \approx \mathbf{f}(\mathbf{q}) + J_f(\mathbf{q}) \Delta \mathbf{q}$$

601.455/655 Copyright R. H. Taylor 1999-2021

12

## Parameter estimation: least squares adjustment

Generally, these are iterative methods. One typical example is:

$$\bar{\mathbf{q}}^* = \operatorname{argmin}_k \sum \left( \bar{\mathbf{f}}(\bar{\mathbf{x}}_k; \bar{\mathbf{q}}) - \bar{\mathbf{p}}_k \right)^2$$

Step 0 Make an initial guess  $\bar{\mathbf{q}}^{(0)}$  of the parameter vector  $\bar{\mathbf{q}}$ . Set  $i \leftarrow 0$ .

Step 1 Solve the least squares problem

$$\begin{bmatrix} \vdots \\ J_{\mathbf{f}}(\bar{\mathbf{q}}^{(i)}) \\ \vdots \end{bmatrix} \Delta \bar{\mathbf{q}}^{(i+1)} \cong \begin{bmatrix} \vdots \\ \bar{\mathbf{p}}_k^* - \bar{\mathbf{f}}(\bar{\mathbf{q}}^{(i)}) \\ \vdots \end{bmatrix} \text{ to find } \Delta \bar{\mathbf{q}}^{(i+1)}$$

Step 2  $\bar{\mathbf{q}}^{(i+1)} \leftarrow \bar{\mathbf{q}}^{(i)} + \Delta \bar{\mathbf{q}}^{(i+1)}$ ; evaluate  $\{\bar{\mathbf{e}}_k \leftarrow \bar{\mathbf{p}}_k^* - \bar{\mathbf{f}}(\bar{\mathbf{q}}^{(i+1)})\}$ ;  $\zeta^{(i+1)} \leftarrow \sum_k \bar{\mathbf{e}}_k \cdot \bar{\mathbf{e}}_k$

Step 3 If  $\zeta^{(i+1)}$  is small enough, or otherwise converged, then stop.

Else set  $i \leftarrow i + 1$  and go back to Step 1.

601.455/655 Copyright R. H. Taylor 1999-2021

13

## Linear Least Squares

- Most commonly used method for parameter estimation
- Many numerical libraries
- See the web site
- Here is a quick review


[Click Here](#)

**Note:** There are many statistics-based methods as well. E.g., Bayesian regression, multivariate Bayesian regression

601.455/655 Copyright R. H. Taylor 1999-2021

14


## Example: 2 link robot calibration



601.455/655 Copyright R. H. Taylor 1999-2021

15

## Example: 2 link robot calibration



601.455/655 Copyright R. H. Taylor 1999-2021

16

## Example: 2 link robot calibration

$$\mathbf{p} = \begin{bmatrix} a_1 \sin \theta_1 + a_2 \sin(\theta_{12}) \\ 0 \\ a_1 \cos \theta_1 + a_2 \cos(\theta_{12}) \end{bmatrix} \quad \text{where } \theta_{12} = \theta_1 + \theta_2$$

$$\mathbf{p}^* = \begin{bmatrix} (a_1 + \Delta a_1) \sin(\theta_1 + \Delta \theta_1) + (a_2 + \Delta a_2) \sin(\theta_{12} + \Delta \theta_1 + \Delta \theta_2) \\ 0 \\ (a_1 + \Delta a_1) \cos(\theta_1 + \Delta \theta_1) + (a_2 + \Delta a_2) \cos(\theta_{12} + \Delta \theta_1 + \Delta \theta_2) \end{bmatrix}$$

601.455/655 Copyright R. H. Taylor 1999-2021

17

## Example: 2 link robot calibration

$$\mathbf{p}_k = \mathbf{f}(\mathbf{q}_k) = \mathbf{f}(a_1, a_2, \theta_1, \theta_2) = \begin{bmatrix} a_1 \sin \theta_{1,k} + a_2 \sin(\theta_{12,k}) \\ 0 \\ a_1 \cos \theta_{1,k} + a_2 \cos(\theta_{12,k}) \end{bmatrix} \quad \text{where } \theta_{12} = \theta_1 + \theta_2$$

so we solve the least squares problem

$$\begin{bmatrix} \vdots & \vdots & \vdots & \vdots & \vdots \\ \frac{\partial \mathbf{f}}{\partial a_1}(\mathbf{q}_k) & \frac{\partial \mathbf{f}}{\partial a_2}(\mathbf{q}_k) & \frac{\partial \mathbf{f}}{\partial \theta_1}(\mathbf{q}_k) & \frac{\partial \mathbf{f}}{\partial \theta_2}(\mathbf{q}_k) & \begin{bmatrix} \Delta a_1 \\ \Delta a_2 \\ \Delta \theta_1 \\ \Delta \theta_2 \end{bmatrix} \\ \vdots & \vdots & \vdots & \vdots & \end{bmatrix} \approx \mathbf{p}_k - \begin{bmatrix} \vdots \\ \mathbf{p}^* - \begin{bmatrix} a_1 \text{Rot}(\mathbf{y}, \theta_{1,k}) \\ + a_2 \text{Rot}(\mathbf{y}, \theta_{1,k}) \end{bmatrix} \\ \vdots \end{bmatrix}$$

601.455/655 Copyright R. H. Taylor 1999-2021

18

## Example: 2 link robot calibration

Here


$$J_f(\mathbf{q}_k) = \begin{bmatrix} \sin \theta_{1,k} & \sin \theta_{12,k} & a_1(\cos \theta_{1,k} + \cos \theta_{12,k}) & a_2 \cos \theta_{12,k} \\ 0 & 0 & 0 & 0 \\ \cos \theta_{1,k} & \cos \theta_{12,k} & -a_1(\sin \theta_{1,k} + \sin \theta_{12,k}) & -a_2 \cos \theta_{12,k} \end{bmatrix}$$

so

$$\begin{bmatrix} \sin \theta_{1,k} & \sin \theta_{12,k} & a_1(\cos \theta_{1,k} + \cos \theta_{12,k}) & a_2 \cos \theta_{12,k} \\ \cos \theta_{1,k} & \cos \theta_{12,k} & -a_1(\sin \theta_{1,k} + \sin \theta_{12,k}) & -a_2 \cos \theta_{12,k} \end{bmatrix} \begin{bmatrix} \Delta a_1 \\ \Delta a_2 \\ \Delta \theta_1 \\ \Delta \theta_2 \end{bmatrix} \approx \begin{bmatrix} \vdots \\ x_k' - a_1 \sin \theta_{1,k} + a_2 \sin(\theta_{12,k}) \\ \vdots \\ z_k' - a_1 \cos \theta_{1,k} + a_2 \cos(\theta_{12,k}) \\ \vdots \end{bmatrix}$$

600.445 Copyright © R. H. Taylor 1999-2008

19




600.445 Copyright © R. H. Taylor 1999-2008

20


## Example: Robodoc Wrist Calibration

- Basic robot in the initial IBM prototype had very accurate calibration
- Custom wrist was less accurate
- Crucial goal was to determine position of cutter tip



600.445 Copyright © R. H. Taylor 1999-2008

21



600.445 Copyright © R. H. Taylor 1999-2008

22

## Kinematic Model

$$\mathbf{p}_{tool} = \mathbf{p}_{wrist} + \mathbf{R}(\mathbf{z}, \theta_4 + \Delta\theta_4) \bullet (\alpha \mathbf{x} + \mathbf{v}_{distal})$$

$$\mathbf{v}_{distal} = \mathbf{R}(\mathbf{x}, \beta) \bullet [\mathbf{R}(\mathbf{y}, \theta_5 + \Delta\theta_5)(\mathbf{v}_c + \Delta\mathbf{v}_c)]$$

600.445 Copyright © R. H. Taylor 1999-2008

23

## Linearization


$$\mathbf{p}_{post} \approx \mathbf{p}_{wrist} + [\mathbf{R}_4 \mathbf{R}_5 (\mathbf{v}_c + \Delta\mathbf{v}_c)] + \dots$$

600.445 Copyright © R. H. Taylor 1999-2008

24

•12

## Example: Undistorted fluoroscope calibration



600.445 Copyright © R. H. Taylor 1999-2008

25

## Calibration if no distortion (version 1)


Assume no distortion. For the moment also assume that you have  $N$  point calibration features (e.g., small steel balls) at known positions  $\{\mathbf{a}_0, \dots, \mathbf{a}_{N-1}\}$  relative to the detector.

Assume further that the points create images at corresponding points  $\{\mathbf{d}_0, \dots, \mathbf{d}_{N-1}\}$  on the detector. Estimate the position  $\mathbf{s}$  of the x-ray source relative to the detector

600.445 Copyright © R. H. Taylor 1999-2008

26


## Approach



600.445 Copyright © R. H. Taylor 1999-2008

27

## Projection of a point feature



600.445 Copyright © R. H. Taylor 1999-2008

28

**Approach**

$(\mathbf{a} - \mathbf{d}) \times (\mathbf{s} - \mathbf{d}) = \mathbf{0}$

$$\begin{aligned} \text{skew}(\mathbf{a} - \mathbf{d}) \cdot \mathbf{s} &= (\mathbf{a} - \mathbf{d}) \times \mathbf{d} \\ &= \mathbf{a} \times \mathbf{d} - \mathbf{d} \times \mathbf{d} \\ &= \mathbf{a} \times \mathbf{d} \end{aligned}$$

$$\left[ \begin{array}{ccc} 0 & \mathbf{d}_z - \mathbf{a}_z & \mathbf{a}_y - \mathbf{d}_y \\ \mathbf{a}_z - \mathbf{d}_z & 0 & \mathbf{d}_x - \mathbf{a}_x \\ \mathbf{d}_y - \mathbf{a}_y & \mathbf{a}_x - \mathbf{d}_x & 0 \end{array} \right] \mathbf{s} = \mathbf{a} \times \mathbf{d}$$

600.445 Copyright © R. H. Taylor 1999-2008

29

**Approach**

Solve least squares problem


$$\left[ \begin{array}{c} \text{skew}(\mathbf{a}_0 - \mathbf{d}_0) \\ \vdots \\ \text{skew}(\mathbf{a}_{N-1} - \mathbf{d}_{N-1}) \end{array} \right] \begin{bmatrix} \mathbf{s}_x \\ \mathbf{s}_y \\ \mathbf{s}_z \end{bmatrix} \equiv \left[ \begin{array}{c} \mathbf{a}_0 \times \mathbf{d}_0 \\ \vdots \\ \mathbf{a}_{N-1} \times \mathbf{d}_{N-1} \end{array} \right]$$

600.445 Copyright © R. H. Taylor 1999-2008


30

## Typical fiducial objects

Points



Curves



FTRAC  
(Jain et al.)

600.445 Copyright © R. H. Taylor 1999-2008

31


## What if pose of calibration object is imprecisely known?

- This is a hairier problem, but solvable
- In fact, it makes a great homework assignment ....

600.445 Copyright © R. H. Taylor 1999-2008

32


## Calibrating trackers to robots and similar “AX = XB” problems



33

**Problem:** How do you determine

$F_{rob}$  and  $F_{wc}$ ?




34

To simplify this situation, define

$$\mathbf{F}_{hw,k} = \mathbf{F}_{h,k}^{-1} \mathbf{F}_{wrist,k}$$

This gives

$$\mathbf{F}_{hc,k} = \mathbf{F}_{hw,k} \mathbf{F}_{wc} = \mathbf{F}_{rob} \mathbf{F}_{rc,k}$$



600.445 Copyright © R. H. Taylor 1999-2008

35

Move the robot to a sequence of poses

$\mathbf{F}_{rc,k}$  for  $k = 0, \dots, N$  and observe the corresponding values of  $\mathbf{F}_{hw,k}$ . Define

$$\mathbf{A}_k = \mathbf{F}_{hw,k} \mathbf{F}_{hw,0}^{-1} \text{ for } k = 1, \dots, N$$

$$\mathbf{B}_k = \mathbf{F}_{rc,k} \mathbf{F}_{rc,0}^{-1} \text{ for } k = 1, \dots, N$$


$\mathbf{A}_k$  represents motion from an initial pose

$$\mathbf{A}_k \mathbf{F}_{hw,0} = \mathbf{F}_{hw,k}$$

so


$$\mathbf{A}_k = \mathbf{F}_{hw,k} \mathbf{F}_{hw,0}^{-1}$$

and similarly for  $\mathbf{B}_k$




600.445 Copyright © R. H. Taylor 1999-2008


36




37




38




39



40



41



42

## Solving “AX = XB” problems where X is a rigid transformation

Given known frame transformations  $\{\mathbf{F}_{A,k}, \mathbf{F}_{B,k}\}$  we want to find a best estimate  $\mathbf{F}_x = [\mathbf{R}_x, \vec{\mathbf{p}}_x]$  such that  $\mathbf{F}_{A,k} \bullet \mathbf{F}_x \approx \mathbf{F}_x \bullet \mathbf{F}_{B,k}$ . This is equivalent to

$$\begin{aligned}\mathbf{R}_{A,k} \mathbf{R}_x &\approx \mathbf{R}_x \mathbf{R}_{B,k} \\ \mathbf{R}_{A,k} \vec{\mathbf{p}}_x + \vec{\mathbf{p}}_{A,k} &\approx \mathbf{R}_x \vec{\mathbf{p}}_{B,k} + \vec{\mathbf{p}}_x\end{aligned}$$

We will solve first for the rotation part and then for the translation part.

600.445 Copyright © R. H. Taylor 1999-2008

44

## Rotation Part (less good way)

**Note: The quaternion method (discussed next) is better**

We want to solve

$$\mathbf{R}_{A,k} \mathbf{R}_x \approx \mathbf{R}_x \mathbf{R}_{B,k}$$

Using the notation

$$\mathbf{R}_A = Rot(\vec{\alpha}) = Rot\left(\frac{\vec{\alpha}}{\|\vec{\alpha}\|}, \|\vec{\alpha}\|\right) = Rot(\vec{\mathbf{n}}_A, \theta_A)$$

etc., we recall that

$$\mathbf{R}_A \mathbf{R}_x = Rot(\vec{\mathbf{n}}_A, \theta_A) \mathbf{R}_x = \mathbf{R}_x Rot(\mathbf{R}_x^{-1} \vec{\mathbf{n}}_A, \theta_A)$$

So

$$\mathbf{R}_x Rot(\mathbf{R}_x^{-1} \vec{\mathbf{n}}_A, \theta_A) = \mathbf{R}_x Rot(\vec{\mathbf{n}}_B, \theta_B)$$

600.445 Copyright © R. H. Taylor 1999-2008

45

## Rotation Part (less good way), continued

From previous slide

$$\mathbf{R}_x \text{Rot}(\mathbf{R}_x^{-1} \vec{\mathbf{n}}_A, \theta_A) = \mathbf{R}_x \text{Rot}(\vec{\mathbf{n}}_B, \theta_B)$$

Multiplying both sides by  $\mathbf{R}_x^{-1}$  gives

$$\text{Rot}(\mathbf{R}_x^{-1} \vec{\mathbf{n}}_A, \theta_A) = \text{Rot}(\vec{\mathbf{n}}_B, \theta_B)$$

This can be expressed as

$$\mathbf{R}_x^{-1} \vec{\alpha} = \vec{\beta}$$

where  $\vec{\alpha} = \theta_A \vec{\mathbf{n}}_A$  and  $\vec{\beta} = \theta_B \vec{\mathbf{n}}_B$ . Rearranging and inserting subscripts gives a system

$$\mathbf{R}_x \vec{\beta}_k = \vec{\alpha}_k$$

which can be solved for  $\mathbf{R}_x$  by standard rigid rotation estimation methods .

600.445 Copyright © R. H. Taylor 1999-2008

46

## Rotation Part (with quaternions)

Let  $\mathbf{q}_x = s_x + \vec{\mathbf{v}}_x$  be the unit quaternion corresponding to  $\mathbf{R}_x$ , with similar definitions for  $\mathbf{q}_A$  and  $\mathbf{q}_B$ . Then we have for  $\mathbf{R}_A \mathbf{R}_x = \mathbf{R}_x \mathbf{R}_B$

$$\mathbf{q}_A \mathbf{q}_x = \mathbf{q}_x \mathbf{q}_B$$

Expanding the scalar and vector parts gives

$$\begin{aligned} s_A s_x - \vec{\mathbf{v}}_A \bullet \vec{\mathbf{v}}_x &= s_x s_B - \vec{\mathbf{v}}_x \bullet \vec{\mathbf{v}}_B \\ s_A \vec{\mathbf{v}}_x + s_x \vec{\mathbf{v}}_A + \vec{\mathbf{v}}_A \times \vec{\mathbf{v}}_x &= s_x \vec{\mathbf{v}}_B + s_B \vec{\mathbf{v}}_x + \vec{\mathbf{v}}_x \times \vec{\mathbf{v}}_B \end{aligned}$$

Rearranging ...

$$\begin{aligned} (s_A - s_B) s_x - (\vec{\mathbf{v}}_A - \vec{\mathbf{v}}_B) \bullet \vec{\mathbf{v}}_x &= 0 \\ (\vec{\mathbf{v}}_A - \vec{\mathbf{v}}_B) s_x + (s_A - s_B) \vec{\mathbf{v}}_x + (\vec{\mathbf{v}}_A + \vec{\mathbf{v}}_B) \times \vec{\mathbf{v}}_x &= \vec{0}_3 \end{aligned}$$

600.445 Copyright © R. H. Taylor 1999-2008

47

## Rotation Part (with quaternions, con' d)

Expressing this as a matrix equation

$$\left[ \begin{array}{c|c} (s_A - s_B) & -(\vec{v}_A - \vec{v}_B)^T \\ \hline (\vec{v}_A - \vec{v}_B) & (s_A - s_B)\mathbf{I}_3 + sk((\vec{v}_A + \vec{v}_B)) \end{array} \right] \left[ \begin{array}{c} s_x \\ \vec{v}_x \end{array} \right] = \left[ \begin{array}{c} 0 \\ \vec{0}_3 \end{array} \right]$$

If we now express the quaternion  $\mathbf{q}_x$  as a 4-vector  $\vec{\mathbf{q}}_x = [s_x, \vec{n}_x]^T$ , we can express the  $\mathbf{AX}=\mathbf{AB}$  rotation problem as the system

$$\begin{aligned} \mathbf{M}(\mathbf{q}_A, \mathbf{q}_B) \vec{\mathbf{q}}_x &= \vec{0}_4 \\ \|\vec{\mathbf{q}}_x\| &= 1 \end{aligned}$$

600. 445 Copyright © R. H. Taylor 1999-2008

48

## Rotation Part (with quaternions, con' d)

In general, we have many observations, and we want to solve the problem in a least squares sense:

$$\min \|\mathbf{M}\vec{\mathbf{q}}_x\| \text{ subject to } \|\vec{\mathbf{q}}_x\| = 1$$

where

$$\mathbf{M} = \begin{bmatrix} \mathbf{M}(\mathbf{q}_{A,1}, \mathbf{q}_{B,1}) \\ \vdots \\ \mathbf{M}(\mathbf{q}_{A,n}, \mathbf{q}_{B,n}) \end{bmatrix} \text{ and } n \text{ is the number of observations}$$

Taking the singular value decomposition of  $\mathbf{M}=\mathbf{U}\Sigma\mathbf{V}^T$  reduces this to the easier problem

$$\min \|\mathbf{U}\Sigma\mathbf{V}^T \vec{\mathbf{q}}_x\| = \|\mathbf{U}(\Sigma \vec{\mathbf{y}})\| = \|\Sigma \vec{\mathbf{y}}\| \text{ subject to } \|\vec{\mathbf{y}}\| = \|\mathbf{V}^T \vec{\mathbf{q}}_x\| = \|\vec{\mathbf{q}}_x\| = 1$$

600. 445 Copyright © R. H. Taylor 1999-2008

49

## Rotation Part (with quaternions, con' d)

This problem is just

$$\min \|\Sigma \vec{y}\| = \left\| \begin{bmatrix} \sigma_1 & 0 & 0 & 0 \\ 0 & \sigma_2 & 0 & 0 \\ 0 & 0 & \sigma_3 & 0 \\ 0 & 0 & 0 & \sigma_4 \end{bmatrix} \vec{y} \right\| \text{ subject to } \|\vec{y}\|=1$$

where  $\sigma_i$  are the singular values. Recall that SVD routines return the  $\sigma_i \geq 0$  and sorted in decreasing magnitude. So  $\sigma_4$  is the smallest singular value and the value of  $\vec{y}$  with  $\|\vec{y}\|=1$  that minimizes  $\|\Sigma \vec{y}\|$  is  $\vec{y} = [0, 0, 0, 1]^T$ . The corresponding value of  $\vec{q}_x$  is given by  $\vec{q}_x = \mathbf{V}\vec{y} = \mathbf{V}_4$ . Where  $\mathbf{V}_4$  is the 4th column of  $\mathbf{V}$ .

600.445 Copyright © R. H. Taylor 1999-2008

50

## Displacement part

The displacement part is given by

$$\mathbf{R}_{A,k} \vec{p}_X + \vec{p}_{A,k} \approx \mathbf{R}_X \vec{p}_{B,k} + \vec{p}_X$$

Once we have solved for  $\mathbf{R}_X$ , we can rearrange the system above as


$$(\mathbf{R}_{A,k} - \mathbf{I}) \vec{p}_X \approx \mathbf{R}_X \vec{p}_{B,k} - \vec{p}_{A,k}$$

which we can solve by least squares

600.445 Copyright © R. H. Taylor 1999-2008

51

## Calibrating an Ultrasound Probe




Boctor E, et. al., "A Novel Closed Form Solution For Ultrasound Calibration", ISBI 2004.

600.445 Copyright © R. H. Taylor 1999-2008

52

## Mapping the space


- Compare observed system performance to reference standard (“ground truth”)
- Interpolate residual errors



600.445 Copyright © R. H. Taylor 1999-2008

53


## Example: Fluoroscope calibration



600.445 Copyright © R. H. Taylor 1999-2008

54

## Projection of a point feature with distortion





600.445 Copyright © R. H. Taylor 1999-2008

55

## C-arm Calibration: Motivation

- Rectify (dewarp) geometric distortions in acquired images.
- Determine the geometry of cone-beam projection
- Compute calibration for each acquired x-ray




Prior studies: Boone et al., 1991; Fahrig et al., 1997;  
Yaniv et al., 1998; Yao, 2002; Daly et al., 2008; ...


Sadowsky, 2008

56

## C-arm Calibration: Instruments, Methods and Results



Initial x-ray phantom




Vertical grid lines detected  
(horizontal follows)




Calibration phantom mounted on  
image intensifier


Phantom Design: Iulian Iordachita, Ofri Sadowsky Russ Taylor



Rectified phantom image



Diamond patterns detected  
→ cone-beam parameters



Sadowsky, 2008

57


## Interpolation

- Ubiquitous throughout CIS research and applications
- Many techniques and methods
- Here are a few more notes

[Click here for  
Interpolation.ppt](#)


58

## Dewarping Method




600.445 Copyright © R. H. Taylor 1999-2008

59



600.445 Copyright © R. H. Taylor 1999-2008


60



600.445 Copyright © R. H. Taylor 1999-2008

61


## Experimental Setup



600.445 Copyright © R. H. Taylor 1999-2008

62

## Dewarping Method




600.445 Copyright © R. H. Taylor 1999-2008


63

## Intrinsic Image Calibration

- Intrinsic imaging parameters (Schreiner et. al.)
- Image Warping (Checkerboard Based Method)



Top View




Side View

600.445 Copyright © R. H. Taylor 1999-2008

64

## Step 0: Acquire Image




600.445 Copyright © R. H. Taylor 1999-2008

65

## Step 1: Find groove points

- Find image points corresponding to the centerline of each vertical and horizontal groove




600. 445 Copyright © R. H. Taylor 1999-2008

66

## Step 2: Fit 5' th order Bernstein Polynomial Curves

- Fit least square smooth curve to each vertical and horizontal groove
- 5' th order Bernstein Polynomial

$$B(a_0, \dots, a_5; v) = \sum_{k=0}^5 a_k \binom{5}{k} (1-v)^{5-k} v^k$$




600. 445 Copyright © R. H. Taylor 1999-2008

67

## Step 3: Dewarp

- Employ a two pass scan line algorithm to dewarp the image



600.445 Copyright © R. H. Taylor 1999-2008


68

## Advantages


- **Fast**
  - < 2 seconds on Pentium II 400
- **Robust**
  - works well even with overlaid objects
- **Sub-pixel Accuracy**
  - mean error 0.12 mm on the central area
- **Does not completely obscure the image**
  - trades off image contrast depth for image area

600.445 Copyright © R. H. Taylor 1999-2008

69




70



71

## Two Plane Method




- E.g., Lavallee
- E.g., Helm

600.445 Copyright © R. H. Taylor 1999-2008

72

## Two Plane Method



Given  $\mathbf{q}$  = a point in image coordinates,  
determine the points

$\mathbf{f}_1^*$  = the point on grid 1 corresponding to  $\mathbf{q}$

$\mathbf{f}_2^*$  = the point on grid 2 corresponding to  $\mathbf{q}$

The desired ray in space passes through  $\mathbf{f}_1^*$   
and  $\mathbf{f}_2^*$ .

600.445 Copyright © R. H. Taylor 1999-2008


73

## Two plane calibration

- Again, the essential problem is to determine the coordinates in the two planes at which the source-to-detector ray passes through the plane.
- Many methods for this. E.g.,
  - Find the four surrounding bead locations on each plane and use bilinear interpolation
  - Fit a general spline model for the distortion on each plane and then directly interpolate

600.445 Copyright © R. H. Taylor 1999-2008

74



Spheres  $i, j$ :  
physical location in plate =  $\vec{b}_{ij}$   
Image location =  $\vec{u}_{ij}$


What are the physical  
coordinates in the plate  
associated with image  
coordinates  $\vec{u}_t$ ?

Photos: Sofamor Danek


```
[λ, μ] ← solve(vec{u}_t = bilinear(λ, μ, {vec{u}_ij}))  
vec{b}_t ← bilinear(λ, μ, {vec{b}_ij})
```

600.445 Copyright © R. H. Taylor 1999-2008

75




76



77

## Calibration with Neural Nets

- Becoming popular in cases where unmodeled system is very complicated or ill-behaved
- Versatile
- Typically have large numbers of model parameters (weights)
- Can require extensive training data
- Training can be computationally expensive



601.455/655 Copyright R. H. Taylor 1999-2023